

MOS FIELD EFFECT TRANSISTOR 2SK3297

SWITCHING N-CHANNEL POWER MOS FET INDUSTRIAL USE

DESCRIPTION

The 2SK3297 is N-channel DMOS FET device that features a low gate charge and excellent switching characteristics, and designed for high voltage applications such as switching power supply, AC adapter.

ORDERING INFORMATION

PART NUMBER	PACKAGE
2SK3297	Isolated TO-220

FEATURES

•Low gate charge

 $Q_G = 18 \text{ nC TYP.}$ ($V_{DD} = 450 \text{ V}$, $V_{GS} = 10 \text{ V}$, $I_D = 5.0 \text{ A}$)

- •Gate voltage rating ±30 V
- •Low on-state resistance

RDS(ON) = 1.6Ω MAX. (VGS = 10 V, ID = 2.5 V)

- Avalanche capability ratings
- •Isolated TO-220 package

(Isolated TO-220)



ABSOLUTE MAXIMUM RATINGS (TA = 25°C)

Drain to Source Voltage (Vgs = 0 V)	VDSS	600	V
Gate to Source Voltage (VDS = 0 V)	Vgss	±30	V
Drain Current(DC) (Tc = 25°C)	I _{D(DC)}	±5.0	Α
Drain Current(pulse) Note1	D(pulse)	±20	Α
Total Power Dissipation (T _A = 25°C)	P _{T1}	2.0	W
Total Power Dissipation (Tc = 25°C)	P _{T2}	35	W
Channel Temperature	Tch	150	°C
Storage Temperature	T_{stg}	-55 to +150	°C
Single Avalanche Current Note2	las	5.0	Α
Single Avalanche Energy Note2	Eas	16.7	mJ

Notes1. PW \leq 10 μ s, Duty Cycle \leq 1%

2. Starting T_{ch} = 25°C, V_{DD} = 150 V, R_G = 25 Ω , V_{GS} = 20 \rightarrow 0 V

The information in this document is subject to change without notice. Before using this document, please confirm that this is the latest version.

Not all devices/types available in every country. Please check with local NEC representative for availability and additional information.




ELECTRICAL CHARACTERISTICS (TA = 25°C)


Characteristics	Symbol	Test Conditions	MIN.	TYP.	MAX.	Unit
Zero Gate Voltage Drain Current	Ipss	VDS = 600 V, VGS = 0 V			100	μΑ
Gate Leakage Current	Igss	Vgs = ±30 V, Vps = 0 V			±100	nA
Gate to Source Cut-off Voltage	V _G S(off)	V _{DS} = 10 V, I _D = 1 mA	2.5		3.5	V
Forward Transfer Admittance	y fs	V _{DS} = 10 V, I _D = 2.5 A	1.5			S
Drain to Source On-state Resistance	RDS(on)	Vgs = 10 V, ID = 2.5 A		1.3	1.6	Ω
Input Capacitance	Ciss	Vps = 10 V		750		pF
Output Capacitance	Coss	Vgs = 0 V		130		pF
Reverse Transfer Capacitance	Crss	f = 1 MHz		9.7		pF
Turn-on Delay Time	td(on)	VDD = 150 V, ID = 2.5 A		17		ns
Rise Time	tr	VGS(on) = 10 V		3		ns
Turn-off Delay Time	td(off)	R _G = 10 Ω		37		ns
Fall Time	t _f			10		ns
Total Gate Charge	Q _G	VDD = 450 V		18		nC
Gate to Source Charge	Q _{GS}	Vgs = 10 V		4		nC
Gate to Drain Charge	Q _{GD}	ID = 5.0 A		7		nC
Body Diode Forward Voltage	VF(S-D)	IF = 5.0 A, VGS = 0 V		0.9		V
Reverse Recovery Time	trr	IF = 5.0 A, VGS = 0 V		1.4		μs
Reverse Recovery Charge	Qrr	$di/dt = 50 \text{ A}/\mu\text{s}$		5.3		μC


TEST CIRCUIT 1 AVALANCHE CAPABILITY

$\begin{array}{c|c} \text{D.U.T.} \\ \text{RG} = 25 \ \Omega \\ \text{PG.} \\ \hline \\ \text{VGS} = 20 \rightarrow 0 \ \text{V} \\ \end{array} \begin{array}{c} \text{D.U.T.} \\ \hline \\ \text{VDD} \\ \end{array}$




TEST CIRCUIT 2 SWITCHING TIME








TEST CIRCUIT 3 GATE CHARGE




TYPICAL CHARACTERISTICS








FORWARD TRANSFER CHARACTERISTICS



V_{GS} - Gate to Source Voltage - V

FORWARD TRANSFER ADMITTANCE vs. DRAIN CURRENT



DRAIN TO SOURCE ON-STATE RESISTANCE vs. DRAIN CURRENT

4
Pulsed

VGS = 10 V


20 V

1
1
1
10
100


ID - Drain Current - A

C

DRAIN TO SOURCE ON-STATE RESISTANCE vs. CHANNEL TEMPERATURE




SOURCE TO DRAIN DIODE FORWARD VOLTAGE




Vsp - Source to Drain Voltage - V

CAPACITANCE vs. DRAIN TO SOURCE VOLTAGE




V_{DS} - Drain to Source Voltage - V

SWITCHING CHARACTERISTICS





REVERSE RECOVERY TIME vs. DIODE FORWARD CURRENT




Isp - Diode Forward Current - A


DYNAMIC INPUT/OUTPUT CHARACTERISTICS









FORWARD BIAS SAFE OPERATING AREA




TRANSIENT THERMAL RESISTANCE vs. PULSE WIDTH



SINGLE AVALANCHE CURRENT vs. INDUCTIVE LOAD




SINGLE AVALANCHE ENERGY DERATING FACTOR




Starting T $_{\text{ch}}$ - Starting Channel Temperature - $^{\circ}\text{C}$

PACKAGE DRAWING(Unit: mm)

Isolated TO-220 (MP-45F)



EQUIVALENT CIRCUIT



Remark Strong electric field, when exposed to this device, can cause destruction of the gate oxide and ultimately degrade the device operation. Steps must be taken to stop generation of static electricity as much as possible, and quickly dissipate it once, when it has occurred.

7

- The information in this document is current as of November, 2000. The information is subject to change without notice. For actual design-in, refer to the latest publications of NEC's data sheets or data books, etc., for the most up-to-date specifications of NEC semiconductor products. Not all products and/or types are available in every country. Please check with an NEC sales representative for availability and additional information.
- No part of this document may be copied or reproduced in any form or by any means without prior written consent of NEC. NEC assumes no responsibility for any errors that may appear in this document.
- NEC does not assume any liability for infringement of patents, copyrights or other intellectual property rights of third parties by or arising from the use of NEC semiconductor products listed in this document or any other liability arising from the use of such products. No license, express, implied or otherwise, is granted under any patents, copyrights or other intellectual property rights of NEC or others.
- Descriptions of circuits, software and other related information in this document are provided for illustrative
 purposes in semiconductor product operation and application examples. The incorporation of these
 circuits, software and information in the design of customer's equipment shall be done under the full
 responsibility of customer. NEC assumes no responsibility for any losses incurred by customers or third
 parties arising from the use of these circuits, software and information.
- While NEC endeavours to enhance the quality, reliability and safety of NEC semiconductor products, customers
 agree and acknowledge that the possibility of defects thereof cannot be eliminated entirely. To minimize
 risks of damage to property or injury (including death) to persons arising from defects in NEC
 semiconductor products, customers must incorporate sufficient safety measures in their design, such as
 redundancy, fire-containment, and anti-failure features.
- NEC semiconductor products are classified into the following three quality grades:
 - "Standard", "Special" and "Specific". The "Specific" quality grade applies only to semiconductor products developed based on a customer-designated "quality assurance program" for a specific application. The recommended applications of a semiconductor product depend on its quality grade, as indicated below. Customers must check the quality grade of each semiconductor product before using it in a particular application.
 - "Standard": Computers, office equipment, communications equipment, test and measurement equipment, audio and visual equipment, home electronic appliances, machine tools, personal electronic equipment and industrial robots
 - "Special": Transportation equipment (automobiles, trains, ships, etc.), traffic control systems, anti-disaster systems, anti-crime systems, safety equipment and medical equipment (not specifically designed for life support)
 - "Specific": Aircraft, aerospace equipment, submersible repeaters, nuclear reactor control systems, life support systems and medical equipment for life support, etc.

The quality grade of NEC semiconductor products is "Standard" unless otherwise expressly specified in NEC's data sheets or data books, etc. If customers wish to use NEC semiconductor products in applications not intended by NEC, they must contact an NEC sales representative in advance to determine NEC's willingness to support a given application.

(Note)

- (1) "NEC" as used in this statement means NEC Corporation and also includes its majority-owned subsidiaries.
- (2) "NEC semiconductor products" means any semiconductor product developed or manufactured by or for NEC (as defined above).

M8E 00.4