

# XN04407 (XN4407)

## Silicon PNP epitaxial planar transistor

For general amplification

### ■ Features


- Two elements incorporated into one package (Each transistor is separated)
- Reduction of the mounting area and assembly cost by one half

### ■ Basic Part Number of Element

- 2SB0709A (2SB709A) + 2SB0970 (2SB970)


### ■ Absolute Maximum Ratings $T_a = 25^\circ\text{C}$

	Parameter	Symbol	Rating	Unit
Tr1	Collector to base voltage	$V_{CBO}$	-60	V
	Collector to emitter voltage	$V_{CEO}$	-50	V
	Emitter to base voltage	$V_{EBO}$	-7	V
	Collector current	$I_C$	-100	mA
	Peak collector current	$I_{CP}$	-200	mA
Tr2	Collector to base voltage	$V_{CBO}$	-15	V
	Collector to emitter voltage	$V_{CEO}$	-10	V
	Emitter to base voltage	$V_{EBO}$	-7	V
	Collector current	$I_C$	-500	mA
	Peak collector current	$I_{CP}$	-1	A
Total	Total power dissipation	$P_T$	300	mW
	Junction temperature	$T_j$	150	$^\circ\text{C}$
	Storage temperature	$T_{stg}$	-55 to +150	$^\circ\text{C}$



Marking Symbol: ES

Internal Connection



Note) The part number in the parenthesis shows conventional part number.

■ Electrical Characteristics  $T_a = 25^\circ\text{C} \pm 3^\circ\text{C}$

• Tr1


Parameter	Symbol	Conditions	Min	Typ	Max	Unit
Collector to base voltage	$V_{CBO}$	$I_C = -10 \mu\text{A}, I_E = 0$	-60			V
Collector to emitter voltage	$V_{CEO}$	$I_C = -2 \text{mA}, I_B = 0$	-50			V
Emitter to base voltage	$V_{EBO}$	$I_E = -10 \mu\text{A}, I_C = 0$	-7			V
Collector cutoff current	$I_{CBO}$	$V_{CB} = -20 \text{V}, I_E = 0$			-0.1	$\mu\text{A}$
	$I_{CEO}$	$V_{CE} = -10 \text{V}, I_B = 0$			-100	
DC current gain	$h_{FE}$	$V_{CE} = -10 \text{V}, I_C = -2 \text{mA}$	160		460	—
Collector to emitter saturation voltage	$V_{CE(sat)}$	$I_C = -100 \text{mA}, I_B = -10 \text{mA}$		-0.3	-0.5	V
Collector output capacitance	$C_{ob}$	$V_{CB} = -10 \text{V}, I_E = 0, f = 1 \text{MHz}$		2.7		pF
Gain bandwidth product	$f_T$	$V_{CB} = -10 \text{V}, I_E = 1 \text{mA}, f = 200 \text{MHz}$		80		MHz

• Tr2








Parameter	Symbol	Conditions	Min	Typ	Max	Unit
Collector to base voltage	$V_{CBO}$	$I_C = -10 \mu\text{A}, I_E = 0$	-15			V
Collector to emitter voltage	$V_{CEO}$	$I_C = -1 \text{mA}, I_B = 0$	-10			V
Emitter to base voltage	$V_{EBO}$	$I_E = -10 \mu\text{A}, I_C = 0$	-7			V
Collector cutoff current	$I_{CBO}$	$V_{CB} = -10 \text{V}, I_E = 0$			-0.1	$\mu\text{A}$
DC current gain *	$h_{FE1}$	$V_{CE} = -2 \text{V}, I_C = -500 \text{mA}$	100		350	—
	$h_{FE2}$	$V_{CE} = -2 \text{V}, I_C = -1 \text{A}$	60			
Collector to emitter saturation voltage	$V_{CE(sat)}$	$I_C = -400 \text{mA}, I_B = -8 \text{mA}$		-0.16	-0.3	V
Base to emitter saturation voltage	$V_{BE(sat)}$	$I_C = -400 \text{mA}, I_B = -8 \text{mA}$		-0.8	-1.2	V
Collector output capacitance	$C_{ob}$	$V_{CB} = -10 \text{V}, I_E = 0, f = 1 \text{MHz}$		22		pF
Gain bandwidth product	$f_T$	$V_{CB} = -10 \text{V}, I_E = 50 \text{mA}, f = 200 \text{MHz}$		130		MHz

Note) \*: Pulse test






Common characteristics chart



Characteristics chart of Tr1



Characteristics chart of Tr2



## Request for your special attention and precautions in using the technical information and semiconductors described in this book

- (1) An export permit needs to be obtained from the competent authorities of the Japanese Government if any of the products or technologies described in this book and controlled under the "Foreign Exchange and Foreign Trade Law" is to be exported or taken out of Japan.
- (2) The technical information described in this book is limited to showing representative characteristics and applied circuits examples of the products. It neither warrants non-infringement of intellectual property right or any other rights owned by our company or a third party, nor grants any license.
- (3) We are not liable for the infringement of rights owned by a third party arising out of the use of the product or technologies as described in this book.
- (4) The products described in this book are intended to be used for standard applications or general electronic equipment (such as office equipment, communications equipment, measuring instruments and household appliances).  
Consult our sales staff in advance for information on the following applications:
  - Special applications (such as for airplanes, aerospace, automobiles, traffic control equipment, combustion equipment, life support systems and safety devices) in which exceptional quality and reliability are required, or if the failure or malfunction of the products may directly jeopardize life or harm the human body.
  - Any applications other than the standard applications intended.
- (5) The products and product specifications described in this book are subject to change without notice for modification and/or improvement. At the final stage of your design, purchasing, or use of the products, therefore, ask for the most up-to-date Product Standards in advance to make sure that the latest specifications satisfy your requirements.
- (6) When designing your equipment, comply with the guaranteed values, in particular those of maximum rating, the range of operating power supply voltage, and heat radiation characteristics. Otherwise, we will not be liable for any defect which may arise later in your equipment.  
Even when the products are used within the guaranteed values, take into the consideration of incidence of break down and failure mode, possible to occur to semiconductor products. Measures on the systems such as redundant design, arresting the spread of fire or preventing glitch are recommended in order to prevent physical injury, fire, social damages, for example, by using the products.
- (7) When using products for which damp-proof packing is required, observe the conditions (including shelf life and amount of time let standing of unsealed items) agreed upon when specification sheets are individually exchanged.
- (8) This book may be not reprinted or reproduced whether wholly or partially, without the prior written permission of Matsushita Electric Industrial Co., Ltd.