

# SANYO Semiconductors DATA SHEET

An ON Semiconductor Company

# CPH3212 — NPN Epitaxial Planar Silicon Transistor DC / DC Converter Applications

# **Applications**

· Relay drivers, lamp drivers, motor drivers, flash

#### **Features**

- · Adoption of MBIT processes
- · High current capacitance
- · Low collector-to-emitter saturation voltage
- Ultrasmall package facilitates miniaturization in end products (mounting height: 0.9mm)
- · High allowable power dissipation


# **Specifications**

#### Absolute Maximum Ratings at Ta=25°C

	9			
Parameter	Symbol	Conditions	Ratings	Unit
Collector-to-Base Voltage	VCBO		100	V
Collector-to-Emitter Voltage	VCES		100	V
Collector-to-Emitter Voltage	VCEO		50	V
Emitter-to-Base Voltage	VEBO		6	V
Collector Current	IC		5	Α
Collector Current (Pulse)	ICP		7	А
Base Current	ΙΒ		1.2	А
Collector Dissipation	PC	When mounted on ceramic substrate (600mm <sup>2</sup> ×0.8mm)	0.9	W
Junction Temperature	Tj		150	°C
Storage Temperature	Tstg		-55 to +150	°C

#### **Package Dimensions**

unit : mm (typ) 7015A-003




#### **Product & Package Information**

• Package : CPH3

• JEITA, JEDEC : SC-59, TO-236, SOT-23

• Minimum Packing Quantity : 3,000 pcs./reel


## Packing Type: TL



## Marking



#### **Electrical Connection**




#### **SANYO Semiconductor Co., Ltd.**

http://semicon.sanyo.com/en/network

#### Electrical Characteristics at Ta=25°C

Parameter	Symbol	Conditions	Ratings			Unit	
Parameter	Symbol	Conditions	min	typ	max	UIIIL	
Collector Cutoff Current	ICBO	V <sub>CB</sub> =40V, I <sub>E</sub> =0A			0.1	μΑ	
Emitter Cutoff Current	IEBO	V <sub>EB</sub> =4V, I <sub>C</sub> =0A			0.1	μΑ	
DC Current Gain	hFE	V <sub>CE</sub> =2V, I <sub>C</sub> =500mA	200		560		
Gain-Bandwidth Product	fT	V <sub>CE</sub> =10V, I <sub>C</sub> =500mA		330		MHz	
Output Capacitance	Cob	V <sub>CB</sub> =10V, f=1MHz		26		pF	
Collector-to-Emitter Saturation Voltage	V <sub>CE</sub> (sat)	I <sub>C</sub> =2A, I <sub>B</sub> =40mA		100	150	mV	
Base-to-Emitter Saturation Voltage	V <sub>BE</sub> (sat)	I <sub>C</sub> =2A, I <sub>B</sub> =40mA		0.80	1.2	V	
Collector-to-Base Breakdown Voltage	V(BR)CBO	I <sub>C</sub> =10μA, I <sub>E</sub> =0A	100			V	
Collector-to-Emitter Breakdown Voltage	V(BR)CES	IC=100μA, RBE=0Ω	100			V	
Collector-to-Emitter Breakdown Voltage	V(BR)CEO	IC=1mA, RBE=∞	50			V	
Emitter-to-Base Breakdown Voltage	V(BR)EBO	I <sub>E</sub> =10μA, I <sub>C</sub> =0A	6			V	
Turn-On Time	ton			32		ns	
Storage Time	tstg	See specified Test Circuit.		420		ns	
Fall Time	tf			28		ns	


# **Switching Time Test Circuit**





 $I_{C}=20I_{B1}=-20I_{B2}=2.5A$ 

## **Ordering Information**

Device	Device Package		memo	
CPH3212-TL-E	CPH3212-TL-E CPH3		Pb Free	








#### **Embossed Taping Specification**

#### CPH3212-TL-E


## 1. Packing Format


Тур	Carrier Tape	Maximum Number of devices contained (pcs)			Packing format		
	Type	Reel	laner box	Outer box	Inner BOX (C-1)	Outer BOX (A-7)	
	СРНЗ	3, 000	15, 000	90, 000	ABOUT COME CONTRACTOR INCOME.	6 inner boxes contained Dimensions:mm (external) $440 \times 195 \times 210$	



# 2. Taping configuration

#### 2-1. Carrier tape size (unit:mm)







Those with one electrode terminal on the feed hole side ..... TL

# **Outline Drawing**

# CPH3212-TL-E



# Land Pattern Example



- Any and all SANYO Semiconductor Co.,Ltd. products described or contained herein are, with regard to "standard application", intended for the use as general electronics equipment. The products mentioned herein shall not be intended for use for any "special application" (medical equipment whose purpose is to sustain life, aerospace instrument, nuclear control device, burning appliances, transportation machine, traffic signal system, safety equipment etc.) that shall require extremely high level of reliability and can directly threaten human lives in case of failure or malfunction of the product or may cause harm to human bodies, nor shall they grant any guarantee thereof. If you should intend to use our products for new introduction or other application different from current conditions on the usage of automotive device, communication device, office equipment, industrial equipment etc., please consult with us about usage condition (temperature, operation time etc.) prior to the intended use. If there is no consultation or inquiry before the intended use, our customer shall be solely responsible for the use.
- Specifications of any and all SANYO Semiconductor Co.,Ltd. products described or contained herein stipulate the performance, characteristics, and functions of the described products in the independent state, and are not guarantees of the performance, characteristics, and functions of the described products as mounted in the customer's products or equipment. To verify symptoms and states that cannot be evaluated in an independent device, the customer should always evaluate and test devices mounted in the customer's products or equipment.
- SANYO Semiconductor Co.,Ltd. assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all SANYO Semiconductor Co.,Ltd. products described or contained herein.
- Regarding monolithic semiconductors, if you should intend to use this IC continuously under high temperature, high current, high voltage, or drastic temperature change, even if it is used within the range of absolute maximum ratings or operating conditions, there is a possibility of decrease reliability. Please contact us for a confirmation
- SANYO Semiconductor Co.,Ltd. strives to supply high-quality high-reliability products, however, any and all semiconductor products fail or malfunction with some probability. It is possible that these probabilistic failures or malfunction could give rise to accidents or events that could endanger human lives, trouble that could give rise to smoke or fire, or accidents that could cause damage to other property. When designing equipment, adopt safety measures so that these kinds of accidents or events cannot occur. Such measures include but are not limited to protective circuits and error prevention circuits for safe design, redundant design, and structural design.
- In the event that any or all SANYO Semiconductor Co.,Ltd. products described or contained herein are controlled under any of applicable local export control laws and regulations, such products may require the export license from the authorities concerned in accordance with the above law.
- No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, or otherwise, without the prior written consent of SANYO Semiconductor Co., Ltd.
- Any and all information described or contained herein are subject to change without notice due to product/technology improvement, etc. When designing equipment, refer to the "Delivery Specification" for the SANYO Semiconductor Co.,Ltd. product that you intend to use.
- Upon using the technical information or products described herein, neither warranty nor license shall be granted with regard to intellectual property rights or any other rights of SANYO Semiconductor Co.,Ltd. or any third party. SANYO Semiconductor Co.,Ltd. shall not be liable for any claim or suits with regard to a third party's intellectual property rights which has resulted from the use of the technical information and products mentioned above.

This catalog provides information as of June, 2012. Specifications and information herein are subject to change without notice.