

IPS521G

FULLY PROTECTED HIGH SIDE POWER MOSFET SWITCH

Features

- Over temperature protection (with auto-restart)
- Short-circuit protection (current limit)
- Active clamp
- E.S.D protection
- Status feedback
- Open load detection
- Logic ground isolated from power ground

Product Summary

$R_{ds(on)}$	100mΩ (max)
V_{clamp}	50V
I_{Limit}	10A
$V_{open\ load}$	3V


Description

The IPS521G is a fully protected five terminal high side switch with built in short circuit, over-temperature, ESD protection, inductive load capability and diagnostic feedback. The output current is controlled when it reaches I_{lim} value. The current limitation is activated until the thermal protection acts. The over-temperature protection turns off the high side switch if the junction temperature exceeds $T_{shutdown}$. It will automatically restart after the junction has cooled 7°C below $T_{shutdown}$. A diagnostic pin is provided for status feedback of short-circuit, over-temperature and open load detection. The double level shifter circuitry allows large offsets between the logic ground and the load ground.


Truth Table

Op. Conditions	In	Out	Dg
Normal	H	H	H
Normal	L	L	L
Open load	H	H	H
Open load	L	H	H
Over current	H	L (limiting)	L
Over current	L	L	L
Over-temperature	H	L (cycling)	L
Over-temperature	L	L	L

Typical Connection



Package



8 Lead SOIC

IPS521G

International
IR Rectifier

Absolute Maximum Ratings

Absolute maximum ratings indicate sustained limits beyond which damage to the device may occur. All voltage parameters are referenced to GROUND lead. ($T_j = 25^\circ\text{C}$ unless otherwise specified).

Symbol	Parameter	Min.	Max.	Units	Test Conditions
V_{out}	Maximum output voltage	$V_{CC}-50$	$V_{CC}+0.3$	V	
V_{offset}	Maximum logic ground to load ground offset	$V_{CC}-50$	$V_{CC}+0.3$		
V_{in}	Maximum Input voltage	-0.3	5.5		
$I_{in, max}$	Maximum positive IN current	-5	10	mA	
V_{dg}	Maximum diagnostic output voltage	-0.3	5.5	V	
$I_{dg, max}$	Maximum diagnostic output current	-1	10	mA	
$I_{sd cont.}$	Diode max. permanent current (1) ($r_{th} = 125^\circ\text{C}/\text{W}$)	—	1.4	A	
$I_{sd pulsed}$	Diode max. pulsed current (1)	—	10		
ESD1	Electrostatic discharge voltage (Human Body)	—	4	kV	C=100pF, R=1500Ω,
ESD2	Electrostatic discharge voltage (Machine Model)	—	0.5		C=200pF, R=0Ω, L=10μH
P_d	Maximum power dissipation ⁽¹⁾ ($r_{th}=125^\circ\text{C}/\text{W}$)	—	1		
T_j max.	Max. storage & operating junction temp.	-40	+150	°C	
V_{cc} max.	Maximum V_{cc} voltage	—	50	V	

Thermal Characteristics

Symbol	Parameter	Min.	Typ.	Max.	Units	Test Conditions
R_{th1}	Thermal resistance with standard footprint	—	100	—	°C/W	8 Lead SOIC
R_{th2}	Thermal resistance with 1" square footprint	—	80	—		

Recommended Operating Conditions

These values are given for a quick design. For operation outside these conditions, please consult the application notes.

Symbol	Parameter	Min.	Max.	Units
V_{cc}	Continuous V_{cc} voltage	5.5	35	V
V_{IH}	High level input voltage	4	5.5	
V_{IL}	Low level input voltage	-0.3	0.9	
I_{out} $T_c=85^\circ\text{C}$	Continuous output current ($T_{Ambient} = 85^\circ\text{C}$, $T_j = 125^\circ\text{C}$, $R_{th} = 100^\circ\text{C}/\text{W}$)	—	1.6	A
R_{in}	Recommended resistor in series with IN pin	4	6	kΩ
R_{dg}	Recommended resistor in series with DG pin	10	20	

(1) Limited by junction temperature (pulsed current limited also by internal wiring)

Static Electrical Characteristics

($T_j = 25^\circ\text{C}$, $V_{cc} = 14\text{V}$ unless otherwise specified.)

Symbol	Parameter	Min.	Typ.	Max.	Units	Test Conditions
$R_{ds(on)}$ @ $T_j = 25^\circ\text{C}$	ON state resistance $T_j = 25^\circ\text{C}$	—	80	100	$\text{m}\Omega$	$V_{in} = 5\text{V}$, $I_{out} = 5\text{A}$
$R_{ds(on)}$ ($V_{cc} = 6\text{V}$)	ON state resistance @ $V_{cc} = 6\text{V}$	—	80	100		$V_{in} = 5\text{V}$, $I_{out} = 2.5\text{A}$
$R_{ds(on)}$ @ $T_j = 150^\circ\text{C}$	ON state resistance $T_j = 150^\circ\text{C}$	—	125	160		$V_{in} = 5\text{V}$, $I_{out} = 5\text{A}$
$V_{cc \text{ oper.}}$	Operating voltage range	5.5	—	35	V	
$V_{\text{clamp } 1}$	V_{cc} to OUT clamp voltage 1	50	55	—		$I_d = 10\text{mA}$ (see Fig.1 & 2)
$V_{\text{clamp } 2}$	V_{cc} to OUT clamp voltage 2	—	56	65		$I_d = I_{sd}$ (see Fig.1 & 2)
V_f	Body diode forward voltage	—	0.9	1.2	μA	$I_d = 2.5\text{A}$, $V_{in} = 0\text{V}$
$I_{cc \text{ off}}$	Supply current when OFF	—	13	50		$V_{in} = 0\text{V}$, $V_{out} = 0\text{V}$
$I_{cc \text{ on}}$	Supply current when ON	—	0.6	2		$V_{in} = 5\text{V}$
$I_{cc \text{ ac}}$	Ripple current when ON (AC RMS)	—	20	—	μA	$V_{in} = 5\text{V}$
V_{dg}	Low level diagnostic output voltage	—	0.4	—	V	$I_{dg} = 1.6 \text{ mA}$
I_{oh}	Output leakage current	—	50	120	μA	$V_{out} = 6\text{V}$
I_{ol}	Output leakage current	0	—	25		$V_{out} = 0\text{V}$
I_{dg} leakage	Diagnostic output leakage current	—	—	10		$V_{dg} = 5.5\text{V}$
V_{ih}	IN high threshold voltage	—	2.2	3	V	
V_{il}	IN low threshold voltage	1	1.9	—		
$I_{in, \text{ on}}$	On state IN positive current	—	70	200	μA	$V_{in} = 5\text{V}$
$I_{in \text{ hyst.}}$	Input hysteresis	0.1	0.25	0.5	V	

Switching Electrical Characteristics

$V_{cc} = 14\text{V}$, Resistive Load = 2.8Ω , $T_j = 25^\circ\text{C}$, (unless otherwise specified).


Symbol	Parameter	Min.	Typ.	Max.	Units	Test Conditions
T_{don}	Turn-on delay time	—	10	40	μs	See figure 3
T_{r1}	Rise time to $V_{out} = V_{cc} - 5\text{V}$	—	25	60		
T_{r2}	Rise time $V_{cc} - 5\text{V}$ to $V_{out} = 90\%$ of V_{cc}	—	130	200		
$dV/dt \text{ (on)}$	Turn ON dV/dt	—	0.7	2	$\text{V}/\mu\text{s}$	See figure 4
E_{on}	Turn ON energy	—	1500	—	μJ	
T_{doff}	Turn-off delay time	—	35	70		
T_f	Fall time to $V_{out} = 10\%$ of V_{cc}	—	16	50	μs	See figure 4
$dV/dt \text{ (off)}$	Turn OFF dV/dt	—	0.9	3	$\text{V}/\mu\text{s}$	See figure 6
E_{off}	Turn OFF energy	—	250	—	μJ	
T_{diag}	V_{out} to V_{diag} propagation delay	—	5	15	μs	

Protection Characteristics


Symbol	Parameter	Min.	Typ.	Max.	Units	Test Conditions
I _{lim}	Internal current limit	7	10	14	A	V _{out} = 0V
T _{sd+}	Over-temp. positive going threshold	—	165	—	°C	See fig. 2
T _{sd-}	Over-temp. negative going threshold	—	158	—	°C	See fig. 2
V _{sc}	Short-circuit detection voltage (3)	2	3	4	V	See fig. 2
V _{open load}	Open load detection threshold	2	3	4	V	

(3) Referenced to V_{CC}

Functional Block Diagram



Lead Assignments






Figure 1 - Active clamp waveforms




Figure 2 - Protection timing diagram




Figure 3 - Switching times definition (turn-on)
Turn on energy with a resistive or an
inductive load




Figure 4 - Switching times definition (turn-off)

IPS521G

International
IR Rectifier






Figure 7 - $R_{ds(on)}$ ($m\Omega$) Vs V_{cc} (V)




Figure 8 - Normalized $R_{ds(on)}$ ($m\Omega$) Vs T_j (°C)




Figure 9 - Rds(on) (mΩ) Vs Iout (A)




Figure 10 - Max. Iout (A) Vs Load Inductance (uH)




Figure 11 - Max load current (A) Vs Tamb (°C)




Figure 12 - Transient Thermal Impedance (°C/W)
 Vs Time (s)




Figure 13 - I_{lim} (A) Vs T_j (°C)




Figure 14 - E_{on}, E_{off} (μJ) Vs I_{out} (A)




Figure 15 - E_{on} (μJ) Vs Load Inductance (μH)
(see Fig. 3)




Figure 16 - Diag Blanking time (μS) Vs I_{out} (A)
(resistive load - see Fig. 6)




Figure 17 - I_{CC} (mA) Vs V_{CC} (V)

Case Outline - 8 Lead SOIC

