# PFR 850 → 856

## **FAST RECOVERY RECTIFIER DIODES**

- LOW FORWARD VOLTAGE DROP
- HIGH SURGE CURRENT CAPABILITY

#### **APPLICATIONS**

- AC-DC POWER SUPPLIES AND CONVER-TERS
- FREE WHEELING DIODES, etc.



#### DESCRIPTION

Their high efficiency and high reliability combined with small size and low cost make these fast recovery rectifier diodes very attractive components for many demanding applications.

## **ABSOLUTE RATINGS** (limiting values)

Symbol	Parameter	Value	Unit A	
I <sub>FRM</sub>	Repetitive Peak Forward Current t <sub>p</sub> ≤ 20µs			
I <sub>F (AV)</sub>	Average Forward Current*	T <sub>a</sub> = 90°C	3	Α
I <sub>FSM</sub>	Surge non Repetitive Forward Current	t <sub>p</sub> = 10ms Sinusoidal	150	A
Ptot	Power Dissipation*	T <sub>a</sub> = 90°C	3.5	W
T <sub>stg</sub> T <sub>i</sub>	Storage and Junction Temperature Range	- 40 to 175	°C	
TL	Maximum Lead Temperature for Soldering during 10s at 4mm from Case		230	∘C

Symbol	Parameter		PFR				
			851	852	854	856	Unit
V <sub>RRM</sub>	Repetitive Peak Reverse Voltage		100	200	400	600	V
V <sub>RSM</sub>	Non Repetitive Peak Reverse Voltage	75	150	250	450	650	V

#### THERMAL RESISTANCE

Symbol	Parameter	Value	Unit
Ath (j-a)	Junction-ambient*	25	°C/W

<sup>\*</sup> On infinite heatsink with 10mm lead length.

## **ELECTRICAL CHARACTERISTICS**

### STATIC CHARACTERISTICS

Symbol	Test Conditions		Min.	Тур.	Max.	Unit
I <sub>R</sub>	T <sub>j</sub> = 25°C	$V_{R} = V_{RRM}$			10	μΑ
	T <sub>J</sub> = 100°C				500	
V <sub>F</sub>	T <sub>j</sub> = 25°C	I <sub>F</sub> = 3A			1.25	V

## RECOVERY CHARACTERISTICS

Symbol	Test Conditions			Min.	Тур.	Max.	Unit
t <sub>rr</sub>	T <sub>j</sub> = 25°C	I <sub>F</sub> = 1A	PFR 850 → 854			150	ns
	V <sub>R</sub> = 30V	$d_{iF}/dt = -25A/\mu s$	PFR 856			200	
I <sub>RM</sub>	T <sub>j</sub> = 25°C	I <sub>F</sub> = 1A				2	Α
	V <sub>R</sub> = 30V	$d_{iF}/dt = -25A/\mu s$					





Fig.1 Recovered charge versus di<sub>F</sub>/dt (typical values).






Fig.2 - Mean forward current  ${\rm I}_{\rm O}$  versus ambient temperature (maximum values).




Fig. 4 - Mean power dissipation versus mean forward current I for different rectifying types, in the case of : - a resistive load (a = 1.57)

- a capacitive load (a > 1.57)




Fig.5 - Transient thermal impedance junction-ambient for mounting n<sup>o</sup>2 versus pulse duration (L ~ 10 mm)





Fig.3 - Thermal resistance versus lead length (maximum values).


Mounting n° 1 : INFINITE HEATSINK



Mounting n°2 : PRINTED CIRCUIT



Mounting n°3: L = 10 mm R<sub>th</sub> = 55 °C/W







Fig.6 - Non repetitive surge peak forward current versus number of cycles.






Fig.3a/3b - Peak forward current versus peak forward voltage drop.




Fig.8 – Non repetitive surge peak forward current for a sinusoidal pulse with width : t  $\leqslant$  10 ms, and corresponding value of  $I^2t$ .




Fig.9 - Capacity C versus reverse applied voltage  $\rm V_{\mbox{\footnotesize R}}$  (typical values).