

December 2009

SB1245 Ultra Low VF Schottky Barrier Rectifier

Applications

- This device is designed for low voltage, high frequency inverters, free-wheeling and polarity protection applications.
- This is also designed as bypass diode for solar modules.

Features

- UL Flammability Classification 94V-O
- Environment Standards MIL-S-19500/228 Compliant
- Low Power Loss, High Efficiency
- High Surge Capacity
- · Pb-free, RoHS Compliant



DO-201ADCOLOR BAND DENOTES CATHODE

Absolute Maximum Ratings * $T_A = 25$ °C unless otherwise noted

Symbol	Parameter	Value	Units
V_{RRM}	Maximum Recurrent Peak Reverse Voltage	45	V
V _{RMS}	Maximum RMS Voltage	31	V
V _{DC}	Maximum DC Blocking Voltage	45	V
I _{F(AV)}	Maximum Average Forward Current	12	А
I _{FSM}	Peak Forward Surge Current 8.3ms Single Half-Sine-Wave Superimposed on Rated Load (JEDEC Method)	150	А
V _F	Maximum Forward Voltage at I _F =12A	0.55	V
I _R	Maximum DC Reverse Current at Rated V_{DC} T_J =25°C T_J =100°C	0.1 10	mA
l ² t	Rating for Fusing (t<8.3ms)	3.7	A ² sec
T _J	Operating Junction Temperature Range -55 to +150 In DC Forward Mode -55 to +200		°C
T _{STG}	Storage Temperature Range	-55 to +175	°C


^{*} These ratings are limiting values above which the serviceability of any semiconductor device may by impaired.

Thermal Characteristics

Symbol	Parameter	Value	Units
$R_{ hetaJL}$	Typical Thermal Resistance, Junction to Lead	10.5	°C/W

^{*} Temperature read point using thermocouple is at 10mm from case edge.

Typical Performance Characteristics



Lead Temperature [°C]

Figure 1a. Average Forward Current Derating Curve




Figure 2. Reverse Current vs. Reverse Voltage






Figure 4. Forward Voltage vs. Forward Current




Lead Temperature [°C]

Figure 1b. DC Forward Current Derating Curve



Percent of Rated Reverse Voltage [%]


Figure 3. Typical Reverse Characteristics



V_R - Reverse Voltage [V]

Figure 5. Typical Junction Capacitance

Physical Dimensions





NOTES: UNLESS OTHERWISE SPECIFIED

- A) PACKAGE STANDARD REFERENCE:
 JEDEC DO-201 VARIATION AD.
 B) PLASTIC PACKAGE BODY.
 D) ALL DIMENSIONS ARE IN MILLIMETERS.
 E) Øb DIMENSION REPRESENT LIKE BELOW:
 OPTION AD = 1.20MIN TO 1.30MAX
 OPTION AE = 0.94MIN TO 1.07MAX
 E) DRAWING FILE NAME: DO201AREV1





TRADEMARKS

The following includes registered and unregistered trademarks and service marks, owned by Fairchild Semiconductor and/or its global subsidiaries, and is not intended to be an exhaustive list of all such trademarks.

AccuPower™ **FPS™** F-PFS™ Auto-SPM™ FRFET® Build it Now™

Global Power ResourceSM CorePLUS™

CorePOWER™ Green FPS™

CROSSVOLT™ Green FPS™ e-Series™ $\mathsf{G} max^{\mathsf{TM}}$

CTL™ Current Transfer Logic™ EcoSPARK[®]

 $\mathsf{GTO}^{\mathsf{TM}}$ IntelliMAX™ EfficentMax™ ISOPLANAR™ EZSWITCH™* MegaBuck™ $\mathsf{MICROCOUPLER}^{\scriptscriptstyle\mathsf{TM}}$

MicroFET™ MicroPak™ MillerDrive™ Fairchild® MotionMax™ Fairchild Semiconductor® Motion-SPM™ FACT Quiet Series™ FACT® FAST® OPTOLOGIC®

FastvCore™ FETBench™ PDP SPM™

FlashWriter®* Power-SPM™ PowerTrench® PowerXS[™]

Programmable Active Droop™

QFĔT^c QS™ Quiet Series™ RapidConfigure™

Saving our world, 1mW/W/kW at a time™

SmartMax™ SMART START™ SPM® STEALTH™

SuperFET™ SuperSOT™-3 SuperSOT™-6 SuperSOT™-8 SupreMOS™ SyncFET™

Sync-Lock™ SYSTEM® GENERAL

The Power Franchise® puwer TinyBoost™ TinyBuck™ TinyCalc™ TinyLogic[®] TINYOPTO™ TinyPower™ TinyPWM™ TinyWire™ TriFault Detect™ TRUECURRENT™* μSerDes™ UHC

Ultra FRFET™ UniFFT™ VCX^{TM} VisualMax™ XSTM

OPTOPLANAR®

DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION, OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS. THESE SPECIFICATIONS DO NOT EXPAND THE TERMS OF FAIRCHILD'S WORLDWIDE TERMS AND CONDITIONS, SPECIFICALLY THE WARRANTY THEREIN, WHICH COVERS THESE PRODUCTS.

LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION.

- 1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury of the user.
- 2. A critical component in any component of a life support, device, or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

ANTI-COUNTERFEITING POLICY

Fairchild Semiconductor Corporation's Anti-Counterfeiting Policy. Fairchild's Anti-Counterfeiting Policy is also stated on our external website, www.fairchildsemi.com, under Sales Support.

Counterfeiting of semiconductor parts is a growing problem in the industry. All manufacturers of semiconductor products are experiencing counterfeiting of their parts. Customers who inadvertently purchase counterfeit parts experience many problems such as loss of brand reputation, substandard performance, failed applications, and increased cost of production and manufacturing delays. Fairchild is taking strong measures to protect ourselves and our customers from the proliferation of counterfeit parts. Fairchild strongly encourages customers to purchase Fairchild parts either directly from Fairchild or from Authorized Fairchild Distributors who are listed by country on our web page cited above. Products customers buy either from Fairchild directly or from Authorized Fairchild Distributors are genuine parts, have full traceability, meet Fairchild's quality standards for handling and storage and provide access to Fairchild's full range of up-to-date technical and product information. Fairchild and our Authorized Distributors will stand behind all warranties and will appropriately address any warranty issues that may arise. Fairchild will not provide any warranty coverage or other assistance for parts bought from Unauthorized Sources. Fairchild is committed to combat this global problem and encourage our customers to do their part in stopping this practice by buying direct or from authorized distributors.

PRODUCT STATUS DEFINITIONS

Definition of Terms

Definition of Terms					
Datasheet Identification	Product Status	Definition			
Advance Information	Formative / In Design	Datasheet contains the design specifications for product development. Specifications may change in any manner without notice.			
Preliminary	First Production	Datasheet contains preliminary data; supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve design.			
No Identification Needed	Full Production	Datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve the design.			
Obsolete	Not In Production	Datasheet contains specifications on a product that is discontinued by Fairchild Semiconductor. The datasheet is for reference information only.			

Rev. 141

^{*} Trademarks of System General Corporation, used under license by Fairchild Semiconductor.